FBA Series

Chip Ferrite Bead SMD Type

Size 0805

FEATURES

- E}]• Œ µ Ÿ}v •}oµŸ}v (}Œ P v Œ o •]Pv o
- s Œ]}µ• (Œ ‹µ v Ç Z Œ š Œ]•Ÿ • Á]šZ î u]+ Œ vš (šµŒ • (}Œ }µvš Œu •µŒ • P šZ]vP (Œ}u P v Œ o •]Pv o• š} Z]PZr•‰
- rŸîìì ‹µ o].
- K‰ Œ ŸvP š u‰ Œ šµŒ Wrññ£š} =íñì£
-

APPLICATION

-

Dimensions: [mm]



Land Pattern: [mm]



Electrical Properties:

	Impedance @ 100MHz (Ω)		DC Resistance Max. (Ω)	Temperature Rise Current Max. (mA)
		%		
& ìôìñrííìrõìíZ	íí			
& ìôìñríóìròìíZ	íó			
& ìôìñrîòìròìíZ	îò			
& ìôìñrïììròìíZ	ïì			
& ìôìñrðììròìíZ	ðì			
& ìôìñròììrõìíZ	òì			
& ìôìñríîírôìíZ	íîì			
& ìôìñríñírôìíZ	íñì			
& ìôìñrîîíróñíZ	îîì			
& ìôìñrïìíróìíZ	ïìì			
& ìôìñrðóíróìíZ	ðóì			
& ìôìñròìírñìíZ	òìì			
& ìôìñríìîrðìíZ	íìì			
& ìôìñríìîrñìíZ	íìì			
& ìôìñríñîrïñíZ	íñì			
& ìôìñrîìîrîñíZ	îìì			
& ìôìñrîìîrðìíZ	îìì			

KOHER Electronics
F9, No. 4188, Huaning Rd, Minhang District, Shanghai
021-34753361 Contact@kohergroup.com

Typical Electrical Characteristics:


FBA0805-601-501R
1000
800
600
400
200
0
IMPEDANCE( )
1
10
100
1000
FREQUENCY(MHz)


FBA0805-102-501R
1500
1000
500
0
IMPEDANCE( )
1
10
100
1000
FREQUENCY(MHz)

Soldering Reflow:

Packaging Information:

Tape Dimension:

Series	A0 (mm)	B0 (mm)	D (mm)	P0 (mm)	P1 (mm)	W (mm)	K0 (mm)	E (mm)	T (mm)
0805	1.30±0.05	2.10±0.05	1.5±0.1	4.0±0.1	4.0±0.1	8.0±0.3	0.95±0.05	1.75±0.1	0.95±0.05

Peel force of top cover tape:



The peel force of top cover tape shall be between 0.14 to 0.58 N

Reel Dimension：[mm]



Cautions and Warnings:

Storage Conditions：

- The storage period is within 12 months after the completion of production. Be sure to follow the storage conditions (temperature: -5 to 35°C, humidity: 75% RH Max).If the storage period elapses, the soldering of the terminal electrodes may deteriorate.The warranty period is one year.
- Product should not be exposed to environment with high temperature, high humidity, dust, corrosive gas and etc.
- Products should be handled with care to avoid damage or contamination from perspiration and skin oils.
- Please always handle products carefully to prevent any damage caused by dropping down or inappropriate removing.

Operation Instructions:

- Self heating (temperature increase) occurs when the power is turned ON, so the tolerance should be sufficient for the set thermal design.
- Before soldering, be sure to preheat components.The preheating temperature should be set so that the temperature difference between the solder temperature and chip temperature does not exceed 150°C.
- Soldering corrections after mounting should be within the range of the conditions determined in the specifications.If overheated, a short circuit, performance deterioration, or lifespan shortening may occur.
- Generally, Koher might not be familiar with either customer's specific application or actual requests as customer does.As a result customer shall be responsible for checking and confirming whether Koher product with the performance described in the product specification is suitable for using in customer's particular application or not.